

## THULE EUROPOWER

**ALIAS NUMBER** 

**CARTON WEIGHT** 

PALLET WEIGHT

22.5 ka

215.5 ka





**EAN CODE** 

30 kg

18.9 kg

2,2

7313020067308

**MAX WEIGHT PER BIKE** 

FITS WHEEL SIZES UP TO

PRODUCT WEIGHT

## Thule EuroPower 916

The robust and stable two bike carrier designed for heavy and large bikes (e.g. E-bikes, big downhill mountain bikes).

- 1. **UPDATE** -New improved, detachable bike arms (for 22-80 mm round and oval frames)
- 2. High load capacity (2 x 30 kg) enabling transport of heavy E-bikes/Pedelecs.
- 3. Extra-large distance between wheel holders (25 cm) enabling transport of sturdy bikes with large wheel bases.
- 4. Smart foot pedal tilt for easy boot access even with bikes mounted.
- Adjustable one hand coupling with low closing force for easy mounting of carrier.
- 6. Pump buckles with long wheel straps for easy fastening of wheels.
- Preassembled no tools required.
- 8. Carrier lockable on tow bar and all bike positions lockable to carrier (locks included)
- 9. Optional: Thule Loading Ramp 9152 a convenient removable ramp for easy loading and unloading of your bikes.
- 10. City Crash tested.



916020

**MAX NUMBER OF BIKES** 

MAX LOAD 60 kg

22-80 mm

**FITS FRAME DIMENSIONS** 

DISTANCE BETWEEN BIKES ELECTRIC CONNECTOR TYPE

**MEASURES (LENGTH X WIDTH)** 

118 x 63 cm

**CARTON DIMS (LENGTH X WIDTH X HEIGHT)** 

119 x 66 x 26 cm

PALLET DIMS (LENGTH X WIDTH X HEIGHT)

120 x 80 x 220 cm

**PCS PER PALLET** 

**ADDITIONAL ACCESSORIES / OPTIONS** 

•Thule Loading Ramp 9152

Convenient removable ramp for easy loading and unloading of your

•Thule Off-Road Adapter 9042

Adapter for fitting the Thule EuroClassic G6 to cars with exterior spare wheel.

•Thule Bike Frame Adapter 982

For use with sensitive frames (e.g.carbon frames) or odd frame shapes.

•Thule Wall Hanger 9771

For functional storage of bikes and bike carriers. Loads up to 40 kg.

- •Thule AcuTight Knob 528 (1 pack)
- Torque limiter knob that "clicks" when optimal hold is reached.
- •Thule Adapter 9907

Converts the car's 13-pin electrical outlet to a 7-pin.

•Thule "One-Key-System"

Very practical if several lockable Thule products are used (e.g. box, roof rack, ski carrier etc.). All locking-barrels will be replaced so only one key will fit all products. (544 = 4 cylinders + 2 keys, 596 = 6 cylinders + 2 keys, 588 = 8 cylinders + 3 keys, 452 = 12 cylinders + 4 keys).



